



CGM DS11000T GENERATOR 12KVA SINGLE PHASE / THREE PHASE AVR

Product price:

6.435,00 € tax excluded

Product description:

CGM DS11000T GENERATOR 12KVA SINGLE PHASE / THREE PHASE AVR

Three-phase 11 KVA CGM DS11000T Generator with Kohler diesel-powered engine at 3000 rpm, compact and user-friendly, mounted on a fixed base with vibration dampers. The CGM DS11000T Generator consists of a Made in Italy, self-excited alternator with brushes and AVR voltage regulator. The CGM DS11000T Generator has electric start with battery with low fuel consumption in fact it consumes only 2.8 liters/hour at 75% load. This DS11000T Generator is perfect for outdoor use such as construction site use.

The CGM DS11000T Generator is part of the QUIET series in that thanks to the enclosure it has low noise emissions and is supersilenced. This Generator is 3000 rpm, with KOHLER diesel engine with electric start with key and battery. The CGM DS11000T Generator features lower fuel consumption and a longer life expectancy than the gasoline-powered range. The CGM DS11000T 3000 rpm Generator is suitable for emergency use only. Use for more than 6 continuous hours and more than 500 hours per year is not recommended.

Technical characteristics of the CGM DS11000T Generator:

Phase Type: Single Phase / Three Phase

Maximum power: 12.1 KVA / 9.7 KW

Continuous use power: 11 KVA / 8.8 KW

Fuel: Diesel

Voltage: 230 / 400 V

Frequency: 50 Hz

Motor: KOHLER KD425

Emission standard: Not Emitted

Engine speed: 3000 rpm

Starter: Electric



Voltage regulator system: AVR
Consumption: 2.8 Lt/h at 75% load
Tank capacity: 30 Lt
Autonomy: 10.7 h at 75% load
Length: 1070 mm
Width: 610 mm
Height: 900 mm
Weight: 235 Kg

Discover the full range of generators of CGM on our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase
Maximum power three phase (KW): 9.7
Continuous power three phase (KW): 8.8
Maximum power three phase (KVA): 12.1
Continuous power three phase (KVA): 11
Fuel: Diesel
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P - 1 x 230V SCHUKO
Engine: Kohler KD425
Emissions Regulations: Not Emitted
Engine rpm (rpm): 3000
Starting system: Electric
Engine capacity (cm³): 851
Number cylinders: 2
Alternator: Linz or NSM
Poles: 2
Fuel tank capacity (L): 30
Consumption (L/h): 2.8
Running time (h): 10.7
Length (mm): 1070
Width (mm): 610
Height (mm): 900
Dry weight (Kg): 235
Silenced: Yes
Super silenced: Yes
Product type: Generator

Voltage regulator: AVR
Engine manufacturer: Kohler