



CGM C3500



Product price:

837,50 € tax excluded

Product description:

CGM C3500 Singlephase Generator 3,5 KVA

Generator CGM C3500 singlephase 3.5 KVA with Honda engine powered by gasoline STAGE V at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers.

The CGM C3500 Generator is composed by a Made in Italy alternator of Linz or NSM, self-excited without brushes and with voltage regulator **AVR**.

The CGM C3500 generator is equipped with manual recoil start and low fuel consumption, in fact it consumes only 1.1 liters/hour at 75% load for a range of almost 3 hours.

This C3500 generator is perfect for outdoor use such as hobby use.

The CGM C3500 generator is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, rigs, campgrounds, hobbies, construction sites etc. The C3500 3000 RPM generator is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

Technical features of CGM C3500 generator:

Phase type: Single phase

Maximum power: 3.4 KW

Continuous power: 3.1 KW

Maximum power: 3.8 KVA

Continuous power: 3.5 KVA

Fuel: Gasoline

Voltage: 230 V

Frequency: 50 Hz

Motor: HONDA GX200

Emission standard: Stage V

Engine RPM: 3000 rpm



Start: Manual
Voltage regulator system: AVR
Consumption: 1.1 Lt/h at 75% load
Tank capacity: 3.1 Lt
Autonomy: 2.8 h at 75% load
Length: 625 mm
Width: 390 mm
Height: 435 mm
Weight: 38 Kg

Discover the full range reserved for current generators of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding and may be subject to revisions by the manufacturer

Product features:

Phase: Single phase
Maximum power single phase (KW): 3.4
Continuous power single phase (KW): 3.1
Maximum power single phase (KVA): 3.8
Continuous power single phase (KVA): 3.5
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230
Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V SCHUKO
Engine: Honda GX200
Emissions Regulations: Stage 5
Engine rpm (rpm): 3000
Starting system: Manual
Engine capacity (cm³): 196
Number cylinders: 1
Alternator: Made in Italy
Poles: 2
Fuel tank capacity (L): 3.1
Consumption (L/h): 1.1
Running time (h): 2.8
Length (mm): 625
Width (mm): 390
Height (mm): 435

Dry weight (Kg): 38

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Honda