



CGM C7000



Product price:

1.462,50 € tax excluded

Product description:

GENERATOR CGM C7000 SINGLE-PHASE 7 KVA

The Generator CGM C7000 single-phase 7 KVA with Honda engine powered by gasoline STAGE V at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The generator is composed of a Made in Italy Linz or NSM alternator, self-excited without brushes and with AVR voltage regulator.

The CGM C7000 generator is equipped with a manual recoil starter but it is also available in the version with electric start and with a low fuel consumption, in fact it consumes only 2 liters/hour at 75% of the load.

This CGM C7000 generator is perfect for outdoor use such as for hobbyist use. The CGM C7000 genset is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, mobile facilities, camping, hobbies, construction sites, etc.

The CGM generator set at 3000 rpm is suitable for emergency use only. It is not recommended for use for more than 6 hours continuously and for more than 500 hours per year.

Technical specifications of CGM C7000 generator:

Phase type: Single phase

Maximum power: 6.9 KW

Continuous power: 6.3 KW

Maximum power: 7.7 KVA

Continuous power: 7 KVA

Fuel: Gasoline

Voltage: 230 V

Frequency: 50 Hz

Engine: HONDA GX390



Engine RPM: 3000 RPM
Start: Manual
Voltage regulator system: AVR
Consumption: 2 Lt/h at 75% load
Tank capacity: 6. 1 Lt
Autonomy: 3 h at 75% load
Length: 780 mm
Width: 510 mm
Height: 500 mm
Weight: 75 Kg

Discover the full range reserved for Generator of CGM or other of the best brands browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase
Maximum power single phase (KW): 6.9
Continuous power single phase (KW): 6.3
Maximum power single phase (KVA): 7.7
Continuous power single phase (KVA): 7
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230
Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE
Engine: Honda GX390
Emissions Regulations: Stage 5
Engine rpm (rpm): 3000
Starting system: Manual
Engine capacity (cm³): 389
Number cylinders: 1
Alternator: Made in Italy
Poles: 2
Fuel tank capacity (L): 6.1
Consumption (L/h): 2
Running time (h): 3
Length (mm): 780
Width (mm): 510

Height (mm): 500
Dry weight (Kg): 75
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: AVR
Engine manufacturer: Honda