



## CGM C11000



Product price:

**2.362,50 € tax excluded**

### Product description:

CGM C11000 single-phase 10 KVA generator

Generator CGM C11000 single-phase 10 KVA generator with Briggs & Stratton engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C11000 generator is composed of a Made in Italy alternator by Linz or NSM, self-excited without brushes and with AVR voltage regulator. The CGM C11000 generator set is equipped with a manual recoil starter, but it is also available in the version with electric start and with a low fuel consumption, in fact it consumes only 3.8 liters/hour at 75% of the load. This generating set C11000 is perfect for outdoor use as for example for hobby use.

The CGM C11000 generating is part of the CLASSIC series and is easily adaptable to various uses such as homes, mobile facilities, camping, hobbies, construction sites, etc.. The C11000 generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

### Technical features of CGM C11000 generator:

Phase type: Single phase

Maximum power: 9.9 KW

Continuous use power: 9 KW

Maximum power: 11 KVA

Continuous use power: 10 KVA

Fuel: Gasoline

Voltage: 230 V

Frequency: 50 Hz

Motor: BRIGGS & STRATTON 16HP

Motor RPM: 3000 RPM

Start: Manual



Voltage regulator system: AVR  
Consumption: 3.8 Lt/h at 75% load  
Tank capacity: 8.5 Lt  
Autonomy: 2.2 h at 75% load  
Length: 910 mm  
Width: 580 mm  
Height: 640 mm  
Weight: 97 Kg

Discover the full range reserved for Ground generators of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

**Product features:**

Phase: Single phase  
Maximum power single phase (KW): 9.9  
Continuous power single phase (KW): 9  
Maximum power single phase (KVA): 11  
Continuous power single phase (KVA): 10  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230  
Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE  
Engine: Briggs&Stratton  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Manual  
Engine capacity (cm<sup>3</sup>): 480  
Number cylinders: 2  
Alternator: Made in Italy  
Poles: 2  
Fuel tank capacity (L): 8.5  
Consumption (L/h): 3.8  
Running time (h): 2.2  
Length (mm): 910  
Width (mm): 580  
Height (mm): 640  
Dry weight (Kg): 97  
Silenced: No  
Super silenced: No  
Product type: Generator

---

ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: Briggs&Stratton