



WFM SE12000-MTHE AVR

Product description:

GENERATOR RENTAL 12KVA AVR SET WFM SE12000-MTHE ELECTRIC GROUP

Generator Rental 12KVA WFM SE12000-MTHE singlephase / threephase generator set equipped with Honda GX690R gasoline engine capable of delivering a maximum power of 12KVA, complete with AVR **voltage regulator**.

Generator Rental 12KVA AVR WFM SE12000-MTHE is a generator set equipped with a protection cabin that makes it super silenced, equipped with electric start, single-phase output of 4KVA and three-phase output of 12 KVA.

RENTAL SERVICE

Generator 12KVA has never been easier: choose the product you want to rent and FILL OUT THE FORM.

Our specialized staff will respond immediately with the offer that best suits you!

The equipment available for rental can be shipped throughout Italy and is always ready for action: our team of technicians will always keep it in perfect working condition.

It is advisable to book in advance for the rental of large quantities of machines: this is especially important in conjunction with trade fairs or events, where many people will be using the rental service.

Voltage Regulator AVR

The Generator 12KVA AVR WFM SE12000-MTHE is equipped with an AVR. The AVR is a device that allows you to **keep the output more constant and less dependent on the load**. Thanks to this card there are fewer drops or spikes in current and this makes it safer to use the

various devices connected, improving performance and durability.

Main Features of Generator Rental 12KVA AVR WFM SE12000-MTHE:

- Soundproof protection frame
- Original Honda or Lombardini engine
- Low oil level protection
- Silencer muffler
- Primary Italian brand alternator
- Electric start with 12V battery
- Full load test with test certificate

TECHNICAL FEATURES WFM SE12000-MTHE

Phase Type: Single-phase / Three-phase
Continuous Singlephase Power: 3.3 KVA / 2.6 KW
Maximum Singlephase Power: 4 KVA / 3.2 KW
Continuous Threephase Power: 10 KVA / 8 KW
Maximum Threephase Power: 12 KVA / 9.6 KW
Factor $\cos \phi$?: 0.8
VAC voltage: 230 / 400 V
Frequency (Hz): 50
Voltage regulator: AVR
Start-up switch: manual
Motor: Honda GX690R
RPM: 3000
Supply: Gasoline
Tank capacity: 20 l
Consumption: 4.6 l/h @ 100 % of load
Autonomy: 4.34 h @ 100 % of load
Acoustic pressure: 67 @ 7m
Length: 1070 mm
Width: 563 mm
Height: 921 mm
Net weight: 210 Kg

Are you looking to rental a generator set with different technical characteristics? Here you can find our entire rental fleet where you can find the perfect generator for you.

Available for Turin and all of Italy.

Images are for guidance only.

**Product features:**

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.2

Continuous power single phase (KW): 2.6

Maximum power single phase (KVA): 4

Continuous power single phase (KVA): 3.3

Maximum power three phase (KW): 9.6

Continuous power three phase (KW): 8

Maximum power three phase (KVA): 12

Continuous power three phase (KVA): 10

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 CEE 5P 400V 16A + 1 CEE 3P 230V 16A

Engine: Honda GX690

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 688

Number cylinders: 2

Oil capacity (L): 1.9

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 4.6 at 100% of the load

Running time (h): 4.34 at 100% of the load

Acoustic power: 92 dB(A)

Acoustic pressure: 67 dB(A)

Length (mm): 1070

Width (mm): 563

Height (mm): 921

Dry weight (Kg): 210

Silenced: Yes

Super silenced: Yes

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Honda

