

GENMAC Click RG6000KO GENERATOR 6,1KVA



Product price:

1.789,00 € tax excluded

Product description:

GENMAC Click RG6000KO SINGLE-PHASE GENERATOR 6,1KVA

The generator Genmac Click RG6000KO single-phase is equipped with a Kohler Diesel powered engine capable of delivering 6,1KVA with capacitor voltage regulator (AVR optional).

High quality Professional Diesel Generators, **Genmac Click Diesel** series with power of **6,1kVA**, are equipped with **Kohler oversized engine** with air-cooled to 3000 RPM.

Professional Genmac Click RG6000KO **diesel generators**, are highly reliable **machines**, built with **quality components** to be **used in professional field**, where reliability is fundamental.

This feature is essential to ensure high reliability of the Genmac Click RG6000KO generator, reduce the effort and increase **the life span by lowering the noise level**.

All **KOHLER** motors **are built using the** best materials, the **most innovative** technics **and the most advanced quality control methods**.

Each engine is carefully tested in order to prove its perfect operation before delivery.

The 6,1KVA generator is equipped with capacitor regulator, on request it can be supplied with AVR.

AVR Voltage Regulator

All models in the Genmac Combipro series are available with optional AVR regulator. The AVR is a device that allows to **maintain the output more constant and less load-dependent**. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving their performance and durability.

The model equipped with AVR card is highly recommended, as it guarantees a significant

improvement in the stability of the output; this feature makes the generators particularly suitable with common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you can enjoy greater stability and thus increase the life of your devices.

TECHNICAL FEATURES OF GENERATOR GENMAC CLICK RG4000KO 6,1KVA

Voltage regulator : capacitor (AVR Optional)

Power supply: Diesel

Starting: Manual

Phase type: Single phase

Continuous power: 5.6KVA / 5.0KW

Maximum power: 6.1KVA / 5.5KW

Motor: Kohler KD15-440

Socket panel: 2 x schuko 16A 230V

Voltage: 230V

Frequency: 50 Hz

3000 rpm

Tank: 5 Lt.

Autonomy @ 75%: 3,7 h fixed rpm

Starting: Manual

Length (mm): 740

Width (mm): 540

Height (mm): 600

Dry weight (Kg): 95

If you are looking for another product then you can see on our catalog other.

Images and technical data are not binding.

Product features:

Phase: Single phase

Maximum power single phase (KW): 5.5

Continuous power single phase (KW): 5

Maximum power single phase (KVA): 6.1

Continuous power single phase (KVA): 5.6

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230

Engine: Kohler KD 15-440

Engine rpm (rpm): 3000

Starting system: Manual

Cooling: Air

Poles: 2

Fuel tank capacity (L): 5

Running time (h): 3.7

Length (mm): 740

Width (mm): 540

Height (mm): 600

Dry weight (Kg): 95

ATS Switch device : No

Voltage regulator: AVR (optional)

Engine manufacturer: Kohler