



Le immagini riportate sono indicative



MOSA GE SX-11000 KDT

Product price:

6.068,00 € tax excluded

Product description:

MOSA GE SX-11000 KDT 8,8 KW Supersilenced Generator AVR

MOSA GE SX-11000 KDT is a single-phase and three-phase 8,8 KW diesel-powered generator set, with Kohler engine, super-silenced and with AVR technology voltage regulator. The MOSA GE SX-11000 KDT is easy to transport thanks to the central lifting hook and has a sealed basement that can contain any leaks of liquids in the engine, thus avoiding environmental pollution.

Even quieter and more efficient than traditional models, the MOSA GE SX-11000 KDT genset delivers a stable and precise three-phase power of 8.8 KW, suitable for powering sophisticated electronic equipment that is sensitive to voltage and frequency variations.

You can therefore quietly and easily enjoy all the little comforts of home wherever you are: lights, fans, a coffee machine, laptops, radio or TV.

The MOSA GE SX-11000 KDT genset is equipped with a 38 litre capacity tank for up to almost 15 hours of continuous operation at 75% load.

The control panel of the MOSA GE SX-11000 KDT genset houses the machine's sockets and controls, including the differential switch, circuit breaker and thermal protection.

A TCM remote control is also available for the MOSA GE SX-11000 KDT genset, allowing the engine to be started/stop up to 10 metres away from the machine.

The MOSA GE SX-11000 KDT genset is suitable for a wide range of uses such as construction, equipment rental, events.

Technical features of the MOSA GE SX-11000 KDT:

Three-phase maximum power: 11 KVA

Three-phase continuous use power: 10 KVA

Maximum power three-phase: 8.8 KW

Three phase continuous use power: 8 KW

Single-phase continuous use power: 6 KVA

Single-phase continuous use power: 6 KW



Fuel: Diesel
Voltage: 230 V / 400 V
Frequency: 50 Hz
Engine: Kohler KDW702
Starting: Electric
Consumption: 2.6 Lt/h at 75% of the load
Length: 1568 mm
Width: 710 mm
Height: 1115 mm
Weight: 340 Kg
Supersilenced
AVR

If you are looking for another product such as MOSA GE SX-11000 KDT generator set then you can browse our catalog for more overland generator sets.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase
Continuous power single phase (KW): 6
Continuous power single phase (KVA): 6
Maximum power three phase (KW): 8.8
Continuous power three phase (KW): 8
Maximum power three phase (KVA): 11
Continuous power three phase (KVA): 10
Fuel: Diesel
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x 400V 16A 3P+N+T CEE IP67 - 2 x 230V 16A 2P+T CEE IP67 - 1 x 230V 16A 2P+T Schuko
Engine: Kohler KDW702
Emissions Regulations: Stage 5
Engine rpm (rpm): 3000
Speed governor: Mechanical
Starting system: Electric
Engine capacity (cm³): 686
Number cylinders: 2
Oil capacity (L): 1.6
Cooling: Water
Alternator: Synchronous self-excited, self-regulated
Fuel tank capacity (L): 38

Consumption (L/h): 2.6
Running time (h): 14.5
Acoustic power: 93 dB(A)
Acoustic pressure: 68 dB(A) at 7 m
Length (mm): 1568
Width (mm): 710
Height (mm): 1115
Dry weight (Kg): 340
Silenced: Yes
Super silenced: Yes
Product type: Generator
ATS Switch device : Optional
Voltage regulator: AVR
Engine manufacturer: Kohler