



# CGM CS11000 SINGLE-PHASE GENERATOR STAGE V 11KVA

Product price:

**5.370,00 € tax excluded**

## Product description:

CGM CS11000 SINGLE-PHASE GENERATOR STAGE V 11KVA

CGM CS11000 single-phase generator of 11KVA with BRIGGS & STRATTON engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use.

The CGM CS17i1000 generator consists of an NSM Made in Italy, self-excited brushless alternator with **AVR** voltage regulator. The generator is equipped with electric start with battery that allows a practical and fast use even when cold. The CGM CS11000 has a low fuel consumption, in fact it consumes only 4,9 liters/hour at 75% of the load.

The CGM CS11000 is part of the QUIET series because thanks to the hood has low noise emissions and is supersilenced. This generator is 3000 rpm, with BRIGGS & STRATTON diesel engine with electric start with key and battery.

## Technical features of the CGM CS11000:

Phase type: Single phase

Maximum power: 10.8KW

Continuous power: 9.9KW

Maximum power: 12KVA

Continuous power: 11KVA

Fuel: Gasoline

Voltage: 230 V

Frequency: 50 Hz

Engine: BRIGGS & STRATTON 21HP

Number of cylinders: 2

Emissions standard: Stage V

Engine RPM: 3000 rpm

Starter: Electric



Alternator: NSM made in Italy  
Voltage regulator system: AVR  
Consumption: 4.9 Lt/h at 75% of the load  
Tank capacity: 50 Lt  
Autonomy: 10,2 h at 75% of the load  
Length: 1100 mm  
Width: 600 mm  
Height: 830 mm  
Weight: 222 Kg  
Supersilence

Discover the full range of current generator from CGM on our catalog to find the one that best suits your needs.

Images and technical data not binding.

**Product features:**

Phase: Single phase  
Maximum power single phase (KW): 10.8  
Continuous power single phase (KW): 9.9  
Maximum power single phase (KVA): 12  
Continuous power single phase (KVA): 11  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230  
Sockets configuration: n.1 presa CEE 16A 3P 230V, n.1 presa CEE 32A 3P 230V, n. 1 presa CEE 63A 3P 230V  
Engine: BRIGGS & STRATTON 21HP  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 627  
Number cylinders: 2  
Alternator: NSM, made in Italy  
Fuel tank capacity (L): 50  
Consumption (L/h): 4.9 @ 75%  
Running time (h): 10.2 al 75% del carico  
Length (mm): 1100

Width (mm): 600

Height (mm): 830

Dry weight (Kg): 222

Silenced: Yes

Super silenced: Yes

Product type: Generator

Voltage regulator: AVR

Engine manufacturer: Briggs&Stratton