



## MASE MARINER 2400 KS SINGLE PHASE SILENCED MARINE GENERATOR 26 KW

**Product price:** 

32.300,00 € tax excluded

## **Product description:**

MASE MARINER 2400 KS SILENCED SINGLE-PHASE MARINE GENERATOR 26 KW

The MASE MARINER 2400 KS Marine Generator Silenced single-phase comes equipped with a KUBOTA V3300 diesel engine capable of delivering a maximum output of 26 KW at 1500 rpm.

Constructed with a synchronous alternator that is self-excited and air-cooled, the MASE MARINER 2400 KS Marine Generator is notably compact and powerful, making it suitable even for small boats.

It provides easy access for maintenance to the power and lubrication systems, seawater pump, air filter, oil filter, and fuel. Furthermore, it features auto-stop safety systems for low oil pressure, high engine temperature, or exhaust gas.

The MASE MARINER 2400 KS's Marine Generator alternator is synchronous, with 4 poles, self-regulated, self-excited, and brushless. In combination with the powerful KUBOTA engine, it can deliver a maximum power of 26 KW. The alternator includes an AVR voltage regulator, ensuring the stability of the output voltage, providing household-like current.

This marine generator MASE MARINER 2400 KS is outfitted with a soundproof cabin that significantly reduces noise, emitting only 54 dB(A) at a distance of 7 meters. The cabin, made of painted aluminum, is extremely lightweight and highly resistant to external elements.

TECHNICAL FEATURES OF MASE MARINER 2400 KS MARINE GENERATOR

Phase Type: Single Phase Maximum Power: 26 KW

Fuel Type: Diesel





Voltage: 115 - 230 V Frequency: 50 Hz

Engine: KUBOTA V3300, 4 Stroke

Mechanical Power: 38.8 Hp Number of Cylinders: 4

Engine Displacement: 3318 cc

Engine RPM: 1500 rpm Fuel Consumption: 11 l/h

Sound Pressure Level: 54 dB(A) @ 7 m Alternator: Synchronous, Brushless

Voltage Regulator: AVR

Dimensions (LxWxH): 1310 mm x 640 mm x 830 mm

Weight: 630 Kg

For those in search of another marine generator, the complete catalog of marine generators is available for browsing.

Note MASE MARINER 2400 KS Marine Generator: Images and technical data provided are indicative and not binding.

Proin nec euismod ligula. Vestibulum ultricies, est sed gravida laoreet, lectus nisi malesuada odio, eget rhoncus purus arcu at augue. Nulla facilisi. Integer id libero ut nibh sollicitudin lacinia quis id arcu. Nunc ullamcorper faucibus sem, ut tempus metus aliquet ut. Suspendisse tristique porttitor libero, in rutrum lorem egestas a. Ut arcu ex, suscipit non orci in, blandit venenatis massa. Morbi sollicitudin sollicitudin laoreet. Nunc bibendum augue vel nulla tempus, ac auctor felis cursus. Quisque consequat nulla justo, sit amet consectetur enim sodales

## **Product features:**

Phase: Single phase

Maximum power single phase (KW): 26

Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 115 / 230

Engine: Kubota V2403, 4 Tempi

Engine rpm (rpm): 1500 Speed governor: Mechanical Engine capacity (cm³): 3318

Number cylinders: 4

Cooling: Air

Alternator: Synchronous, self-excited

Poles: 4

Lubrication: Forced

Consumption (L/h): 7.6 at 100% of the load

Acoustic pressure: 54 dB(A) at 7 m





Length (mm): Width (mm): 640 Height (mm): 830 Dry weight (Kg): 630

Inverter: No AVR: Yes

Compound: No Silenced: Yes

Super silenced: Yes Product type: Generator Voltage regulator: AVR

Engine manufacturer: Kubota

