



LINZ PRO18L F/4 Three-phase alternator 4 poles 60 kVA 60 Hz AVR



Product description:

The alternators of **PRO** series are three-phase brushless 4 poles with electronic regulation (AVR) with single-phase sensing (PRO18-PRO22) and three-phase sensing (PRO28-PRO35-PRO40).

CHARACTERISTICS

- Compact and mechanically resistant
- Excellent wave form
- Minimum maintenance
- High efficiency

- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: AVR
- Application: INDUSTRIAL, COGENERATION

Product features:

Phase: Three phase

Continuous power three phase (KVA): 60

Frequency (Hz): 60

Voltage (V): 230 / 400

Engine rpm (rpm): 1800



Alternator: Synchronous

Poles: 4

Three-phase power (KVA): 50

Protection degree: IP23

Motor insulation class: H

Length (mm): 642

Width (mm): 362

Height (mm): 458

Brushes: No

PMG: No

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 236.5