



GENMAC Whisper-GAS RG10000KS-M5 LPG GENERATOR 10,9KVA

Product description:

GENMAC Whisper-GAS RG10000KS-M5 LPG SINGLE-PHASE GENERATOR 10,9KVA

The Genmac Whisper-GAS RG10000KS-M5 LPG single phase generator is equipped with a Kohler motor powered by LPG gas capable of delivering a power of 10,9KVA with capacitor voltage regulator (AVR optional).

High quality professional silenced three-phase LPG power generator, Genmac with 10.9KVA power. The Genmac LPG generator is equipped with an oversized air-cooled Kohler motor.

Genmac professional LPG generators are highly reliable machines, built with quality components to be used in professional field, where reliability is fundamental.

This feature is fundamental to guarantee a high reliability of the generator, reduces its effort and increases its life span by lowering the noise level.

All Kohler engines are built using the best materials, the most innovative techniques and the most advanced quality control methods.

Each engine is thoroughly tested to prove that it works perfectly before delivery.

In case of need, Kohler service is always at your disposal.

The 10.9KVA generator is equipped with a capacitor voltage regulator, on request it can be supplied with the AVR regulator.

AVR Voltage Regulator

All Genmac series models are available with optional AVR voltage regulator. The AVR is a device that allows to keep the output more constant and less dependent on the load. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving performance and durability.

The model equipped with AVR board is highly recommended, as it guarantees a significant improvement in the stability of the output; this feature makes the generators particularly suitable for common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you will enjoy greater stability and therefore an increase in the life of your devices.

TECHNICAL CHARACTERISTICS OF GENERATOR GENMAC Whisper-GAS RG10000KS-M5 LPG 10,9KVA

Voltage Regulator : Capacitor (AVR Optional)

Power Supply: LPG

Firing: Electric

Phase Type: Single Phase

Continuous Power: 9.9KVA / 8.9KW

Maximum Power: 10.9KVA / 9.8KW

Motor: Kohler CH730

Emission Standard: Stage V

Socket panel: 1 x Schuko 16A 230V / 1 x 32A 230V / 1 x 63A 230V

Voltage: 230V

Frequency: 50 Hz

3000 rpm

Autonomy @ 75%: 5.2 h fixed rpm

Sound pressure: 65 dB(A) @ 7m

Length (mm): 1100

Width (mm): 540

Height (mm): 924

Dry weight (Kg): 278

If you are looking for another product then you can consult other terrestrial generators in our catalog.

Images and technical data are not binding.

Product features:

Phase: Single phase

Maximum power single phase (KW): 9.8

Continuous power single phase (KW): 8.9

Maximum power single phase (KVA): 10.9

Continuous power single phase (KVA): 9.9

Fuel: LPG

Frequency (Hz): 50

Voltage (V): 230



Sockets configuration: 1 x Schuko 16A 230V / 1 x 32A 230V / 1 x 63A 230V

Engine: Kohler CH730

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Electric

Cooling: Air

Poles: 2

LPG consumption (m³/h): 5.2

Acoustic pressure: 65 dB(A) at 7 m

Length (mm): 1100

Width (mm): 540

Height (mm): 924

Dry weight (Kg): 278

Silenced: Yes

Super silenced: Yes

ATS Switch device : Optional

Voltage regulator: Capacitor / AVR (optional)

Engine manufacturer: Kohler

