

MASE MARINER 2806 KS SINGLE PHASE MARINE GENERATOR SILENCED 30KW EPA



Product description:

MASE MARINER 2806 KS SILENCED SINGLE-PHASE MARINE GENERATOR 30 KW EPA

MASE MARINER2806KS single-phase silenced marine generator is equipped with a KUBOTA V3300 Diesel engine with **EPA emissions standard**, capable of delivering a maximum power of 30 KW at 1800 rpm.

The MASE MARINER2806KS alternator is a 4-pole synchronous, self-regulated, self-excited, brushless alternator, which in combination with the powerful KUBOTA engine can deliver a maximum power of 30 KW. The alternator is complete with AVR voltage regulator that ensures the stability of the voltage delivered by the generator, delivering current like the one at home.

The MASE MARINER2806KS allows easy access for maintenance of the alimentation and lubrication systems, seawater pump, air filter, oil filter and fuel. It is also equipped with safety systems of auto stop for low oil pressure and high temperature engine or exhaust gas.

The MASE MARINER2806KS is equipped with a soundproof cabin that makes it super silent, with a sound emission of 56dB(A) at a distance of 7 m. The painted aluminum soundproofing cabin is extremely lightweight and of very high resistance to external agents.

The MASE MARINER2806KS marine generator has **EPA certification** valid only for the **US market**.

TECHNICAL FEATURES MASE MARINER2806KS

Phase Type: Single Phase

Maximum Power: 30 KW

Fuel: Diesel

Voltage: 120 - 240 V

Frequency: 60 Hz
Engine: KUBOTA V3300, 4 Stroke
Emissions Standard: EPA
Mechanical Power: 47.3 Hp
Number of cylinders: 4
Displacement: 3318 cc
Engine RPM: 1800 rpm
Fuel consumption: 13 l/h
Sound pressure: 56 dB(A) @ 7 m
Alternator: Synchronous Brushless
Voltage regulator: AVR
Length: 1310mm
Width: 640 mm
Height: 830 mm
Weight: 630 Kg

If you are looking for another marine generator then you can browse the entire catalog of marine generators.

Images and technical data are not binding.

Product features:

Phase: Single phase
Maximum power single phase (KW): 30
Fuel: Diesel
Frequency (Hz): 60
Voltage (V): 120 / 240
Engine: KUBOTA V3300
Emissions Regulations: EPA
Engine rpm (rpm): 1800
Speed governor: Electronic
Engine capacity (cm³): 3318
Number cylinders: 4
Cooling: Air
Inyección : Indirect
Alternator: Synchronous, self-excited
Poles: 4
Lubrication: Forced
Consumption (L/h): 13 at 100% of the load
Acoustic pressure: 56 dB(A) at 7 m
Length (mm): 1310
Width (mm): 640

Height (mm): 830
Dry weight (Kg): 630
Inverter: No
AVR: Yes
Compound: No
Silenced: Yes
Super silenced: Yes
Voltage regulator: AVR