



## GENSET MG 6/4 I-D/AE-Y SINGLE-PHASE/THREE-PHASE GENERATOR 6,5 KVA

**Product price:** 

2.858,55 € tax excluded

## **Product description:**

GENSET MG 6/4 I-D/AE-Y SINGLE-PHASE/THREE-PHASE GENERATOR 6.5 KVA

GENSET MG 6/4 I-D/AE-Y is a single-phase generating set equipped with a Yanmar L100N StageV engine powered by Diesel, capable of delivering a maximum power of 6.5 KVA.

The GENSET MG 6/4 I-D/AE-Y also has a low fuel consumption: only 1.5 Lt/h at 75% load. The GENSET MG 6/4 I-D/AE-Y generator set, thanks to the high quality and efficiency of its components, is ideal for various types of work: from small hobby work to large construction sites.

The GENSET MG 6/4 I-D/AE-Y generator set is ideal for various types of work: from small hobby work to large construction sites.

The genset is easy to install and operate, as well as simple to start and stop thanks to the clear and intuitive controls. GENSET MG 6/4 I-D/AE-Y is equipped with a Yanmar L100N Diesel engine. They are very reliable engines that guarantee efficient combustion and low fuel consumption, they are also equipped with a protection system that causes the engine to stop if the oil level is too low.

GENSET MG 6/4 I-D/AE-Y are equipped with a 5.5-liter tank with a large cap that is easy to unscrew even with work gloves

GENSET MG 6/4 I-D/AE-Y has an all-steel structure and a large metal tank. The generator guarantees an efficient and silent operation thanks to the Yanmar L100N which allows to deliver a maximum power of 6,5 KVA.

The generator set comes with:





- 1 single-phase socket CEE 16 A 230 V
- 1 three-phase socket CEE 16 A 400 V
- Starter battery
- Hour meter
- Voltmeter
- Low oil pressure and battery charge warning lights
- Power output protection
- Differential circuit breaker
- Arrangement for operation in AMF-ATS or Remote control

## TECHNICAL CHARACTERISTICS GENSET MG 6/4 I-D/AE-Y

Phase Type: Single-Phase / Three-Phase

Maximum Single-Phase Power: 2.1 KVA / 1.7 KW Maximum Single-Phase Power: 6.5 KVA / 5.2 KW

VAC Voltage: 230 / 400 V

Frequency (Hz): 50 Starting Frame: Electric Motor: Yanmar L100V

**Emission Standard: StageV** 

RPM: 3000

Power supply: Diesel Fuel tank capacity: 5.5 l

Consumption @ 75 % load: 1.5 l/h Autonomy @ 75 % load: 3.6 h Sound pressure: 99 dB(A)

Length: 820 mm Width: 580 mm Height: 610 mm Net weight: 110 Kg

Are you looking for a power generator with different characteristics? Here you can find the full range of products GENSET or other brands specializing in the field

Images and technical data are not binding and may be subject to revision by the supplier.

## **Product features:**

Phase: Single phase / Three phase Maximum power single phase (KW): 1.7 Maximum power single phase (KVA): 2.1 Maximum power three phase (KW): 5.2 Maximum power three phase (KVA): 6.5





Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 230

Sockets configuration: 1x CEE 16 A - 230 V 1xCEE 32 A - 230 V

Engine: Yanmar L100N

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000 Starting system: Electric Engine capacity (cm³): 435

Number cylinders: 1

Cooling: Air

Alternator: Synchronous Protection degree: IP23 Motor insulation class: H Fuel tank capacity (L): 5.5 Consumption (L/h): 1.5 Running time (h): 3.6 Acoustic power: 99 dB(A)

Acoustic pressure: 74 dB(A) at 7 m

Length (mm): 820 Width (mm): 580 Height (mm): 610 Dry weight (Kg): 110

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device: Optional

Voltage regulator: Compound / AVR (optional)

Engine manufacturer: Yanmar