

GENERATOR SINGLE-PHASE 12KVA STAGE V



Product price:

2.385,00 € tax excluded

Product description:

GENERATOR SINGLE-PHASE 12 KVA

Single phase 12 KVA generator set with Briggs & Stratton engine powered by STAGE V petrol at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers. The generator set consists of a Made in Italy alternator from Linz or NSM, self-excited without brushes and with optional capacitor or AVR voltage regulator. The generator set is equipped with electric starter and low fuel consumption, in fact it consumes only 4.3 litres/hour at 75% of the load. This generator set is perfect for outdoor use such as hobby use.

The generator set is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, street installations, camping sites, hobbies, construction sites, etc.. The generator set at 3000 rpm is only suitable for emergency use. We do not recommend use for more than 6 consecutive hours and more than 500 hours per year.

Technical characteristics of the generator set:

Phase type: Single-phase

Maximum single-phase power: 11.8 KW

Single-phase continuous use power: 10.8 KW

Maximum single-phase power: 13.2 KVA

Single-phase continuous use power: 12 KVA

Fuel: Gasoline

Voltage: 230 V

Frequency: 50 Hz

Engine: BRIGGS & STRATTON 18HP

Engine revs: 3000 rpm

Starting: Electric

Voltage regulator system: Capacitor, AVR optional

Consumption: 4.3 Lt/h at 75% of the load

Tank capacity: 8.5 Lt

Autonomy: 2 h at 75% of the load

Length: 910 mm
Width: 580 mm
Height: 640 mm
Weight: 125 Kg

Discover the entire range reserved for generators of other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Product features:

Phase: Single phase

Maximum power single phase (KW): 11.8

Continuous power single phase (KW): 10.8

Maximum power single phase (KVA): 13.2

Continuous power single phase (KVA): 12

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE

Engine: Briggs&Stratton

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 570

Number cylinders: 2

Alternator: Made in Italy

Poles: 2

Fuel tank capacity (L): 8.5

Consumption (L/h): 4.3

Running time (h): 2

Length (mm): 910

Width (mm): 580

Height (mm): 640

Dry weight (Kg): 125

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: Capacitor / AVR (optional)