



# GENERATOR SINGLE-PHASE 11KVA AVR STAGEV

Product price:

**3.996,00 € tax excluded**

## Product description:

### GENERATOR SINGLE-PHASE 11KVA AVR STAGEV

Generator single-phase equipped with a Honda GX 630 OHV (STAGE V) gasoline engine capable of delivering a maximum power output of 11KVA.

The generator also has low fuel consumption: only 5.5 liters/hour at 75% load. Thanks to the high quality and efficiency of its components, the generator is ideal for various types of work, from small hobby projects to large construction sites.

The generator is easy to install and operate, with clear and intuitive controls for easy starting and stopping. The generator is powered by a Honda GX 630 OHV gasoline engine **STAGE V**. These engines are highly reliable, ensuring efficient combustion and reduced fuel consumption. They are also equipped with a protection system that shuts down the engine if the oil level is too low.

The generator features a 29-liter tank with a large cap that is convenient to unscrew even while wearing work gloves. It has a fully steel structure and a large metal tank. The generator ensures efficient and quiet operation thanks to the Honda GX 630 OHV engine, which can deliver a maximum power output of 11 KVA.

The generator comes with:

- Automatic shutdown for low oil level
- 12V Battery
- 1 CEE 16A, 230V - 50 Hz single-phase socket
- 1 CEE 32A, 230V - 50 Hz single-phase socket
- Power output protections
- Differential switch
- Voltmeter
- Hour meter
- Central lifting hook



## TECHNICAL SPECIFICATIONS

Phase Type: Single-Phase  
Continuous Power: 10 KVA / 8 KW  
Maximum Power: 11 KVA / 8.8 KW  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Engine: Honda GX 6300 OHV  
Engine Speed: 3000 RPM  
Emission Standards: Stage V  
Startup: Electric  
Voltage Regulator: AVR  
Socket Configuration: 1 x 230V 16A CEE - 1 x 230V 32A CEE  
Consumption: 5.5 l/h  
Tank Capacity: 29 L  
Autonomy: 5.27 h  
Sound Pressure: 73 dB(A) at 7m  
Length: 904 mm  
Width: 507 mm  
Height: 823 mm  
Weight: 148 Kg

Looking for a power generator with different features? [HERE](#) you can find the area dedicated to generators from other brands specializing in the field.

Images and technical data are not binding and may be subject to revisions by the supplier.

### **Product features:**

Phase: Single phase  
Maximum power single phase (KW): 8.8  
Continuous power single phase (KW): 8  
Maximum power single phase (KVA): 11  
Continuous power single phase (KVA): 10  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230  
Sockets configuration: 1 x 230V 16A CEE - 1 x 230V 32A CEE  
Engine: Honda GX630, 4 stroke, OHV  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Electric



---

Engine capacity (cm<sup>3</sup>): 688  
Number cylinders: 2  
Cooling: Air  
Alternator: Synchronous  
Protection degree: IP23  
Motor insulation class: H  
Fuel tank capacity (L): 29  
Consumption (L/h): 5.5  
Running time (h): 5.27  
Acoustic power: 98 dB(A)  
Acoustic pressure: 73 dB(A) at 7 m  
Length (mm): 904  
Width (mm): 507  
Height (mm): 823  
Dry weight (Kg): 148  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Honda