



# GENSET MGF 33 Y Single-Phase/Three-Phase Generator Group Stage V 33KVA AVR

Product price:

**16.030,30 € tax excluded**

## Product description:

GENSET MGF33Y SINGLE-PHASE/THREE-PHASE GENERATOR GROUP STAGE V 33KVA AVR

The GENSET MGF33Y Stage V Generator Set is a perfect solution for those seeking a reliable, quiet, and efficient power source. Equipped with a Yanmar engine operating at 1500 RPM, the GENSET MGF33Y is designed for automatic starting, ensuring simple and efficient operation in any situation.

The openable canopy of the GENSET MGF33Y Stage V Generator Set allows for easy and quick maintenance, while the lifting hook and forkable base facilitate practical and safe handling. With a maximum three-phase power of 33 KVA and a maximum single-phase power of 11 KVA, the GENSET MGF33Y Stage V Generator Set is ideal for a wide range of applications.

## Technical Specifications of the GENSET MGF33Y Stage V Generator Set:

Maximum Three-Phase Power: 33 KVA  
Maximum Three-Phase Power: 26.4 KW  
Maximum Single-Phase Power: 11 KVA  
Maximum Single-Phase Power: 8.8 KW  
Fuel: Diesel  
Voltage: 230/400 V  
Frequency: 50 Hz  
Acoustic Power: 97 Lwa (72 dB at 7 meters)  
Engine: Yanmar 4TNV98 (STAGE V)  
Number of Cylinders: 4

---

Engine Power: 46.1 HP (34.4 kWm)  
Displacement: 3319 cm<sup>3</sup>  
Cooling: Liquid  
Starting: Electric  
Fuel Tank Capacity: 40 liters  
Consumption: 6.4 liters/hour  
Protection Rating: IP23  
Dimensions (L x W x H): 1752 x 835 x 1170 mm  
Weight: 726 kg

**Key Features of the GENSET MGF33Y Stage V Generator Set:**

**Quiet and Efficient:** With an acoustic power of 97 Lwa and only 72 dB at 7 meters, the GENSET MGF33Y

Stage V Generator Set is suitable for environments where noise needs to be minimized.

**Easy Maintenance:** The openable canopy allows quick access for maintenance, making the GENSET MGF33Y Stage V Generator Set very practical to manage.

**Simple Handling:** The lifting hook and forkable base facilitate the transport and installation of the GENSET MGF33Y Stage V Generator Set, ensuring safe handling.

**Automatic Starting:** Designed for automatic starting, enhancing the reliability and convenience of the GENSET MGF33Y Stage V Generator Set.

The GENSET MGF33Y Stage V represents an excellent choice for those needing a powerful, quiet, and easy-to-maintain three-phase generator. Designed to deliver high and lasting performance, the GENSET MGF33Y is ideal for industrial and commercial applications where reliability is crucial. The Yanmar engine, known for its reliability and efficiency, ensures effective operation with reduced fuel consumption, making the GENSET MGF33Y Stage V Generator Set a cost-effective and sustainable choice.

Looking for a power generator with different characteristics? HERE you can find the full range of products from GENSET or other brands specializing in the field

Images and technical data are not binding and may be subject to revision by the supplier.

**Product features:**

Phase: Single phase / Three phase  
Maximum power single phase (KW): 8.8

---

Maximum power single phase (KVA): 11  
Maximum power three phase (KVA): 33  
Continuous power three phase (KVA): 30  
Fuel: Diesel  
Frequency (Hz): 50  
Voltage (V): 400/230  
Sockets configuration: 1 x 400V 16A CEE - 1 x 400V 63A CEE - 2 x 230V 16A CEE  
Engine: Yanmar 4TNV98, 4 stroke  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 1500  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 3319  
Number cylinders: 4  
Cooling: Coolant Liquid  
Protection degree: IP23  
Motor insulation class: H  
Fuel tank capacity (L): 40  
Consumption (L/h): 6.4  
Running time (h): 6.25  
Acoustic power: 97 dB(A)  
Acoustic pressure: 72 dB(A) at 7 m  
Length (mm): 1752  
Width (mm): 835  
Height (mm): 1170  
Dry weight (Kg): 726  
Silenced: Yes  
Product type: Generator  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Yanmar