



# PRAMAC GSW10Y COFANATO CON QUADRO COMANDO MANUALE (MCP)

## Product description:

## Product features:

Phase: Three phase

Maximum power three phase (KW): 140.21

Continuous power three phase (KW): 101.97

Maximum power three phase (KVA): 140.21

Continuous power three phase (KVA): 127.46

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Engine: FPT NEF67SM1A, turbocharged

Speed governor: Mechanical

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 6

Number cylinders: 6

Cylinders' position: In line

Oil capacity (L): 17.2

Cooling: Water

Alternator: Mecc Alte ECP34-1L, brushless

Poles: 4

Fuel tank capacity (L): 240

Consumption (L/h): 21.5 at 75% of the load / 28.2 at 100% of the load

Running time (h): 11.1 at 75% of the load / 8.5 at 100% of the load

Length (mm): 2200

Width (mm): 1000

Height (mm): 1743

Dry weight (Kg): 1441

Inverter: No

AVR: Yes

Compound: No

Silenced: No

Super silenced: No