



# PRAMAC GSW10Y COFANATO CON QUADRO COMANDO MANUALE (MCP)

## Product description:

## Product features:

Phase: Three phase

Maximum power three phase (KW): 131.2

Continuous power three phase (KW): 120.5

Maximum power three phase (KVA): 164

Continuous power three phase (KVA): 150.63

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Engine: PERKINS 1006 TAG2, turbocharged

Speed governor: Electronic

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 5990

Number cylinders: 6

Cylinders' position: In line

Oil capacity (L): 19

Cooling: Water

Alternator: Mecc Alte ECP34-2L, brushless

Poles: 4

Fuel tank capacity (L): 250

Consumption (L/h): 31.5 at 75% of the load / 41 at 100% of the load

Running time (h): 7.9 at 75% of the load / 6.1 at 100% of the load

Length (mm): 2600

Width (mm): 1000

Height (mm): 1600

Dry weight (Kg): 1451

Silenced: No

Super silenced: No

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Perkins