



# PRAMAC GSW10Y COFANATO CON QUADRO COMANDO MANUALE (MCP)

## Product description:

## Product features:

Phase: Three phase

Maximum power three phase (KW): 465.34

Continuous power three phase (KW): 422.02

Maximum power three phase (KVA): 581.68

Continuous power three phase (KVA): 527.52

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Engine: Doosan DP158LD, turbo intercooled

Speed governor: Electronic

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 14618

Cooling: Water

Alternator: Mecc Alte ECO40-1L/4, brushless

Poles: 4

Fuel tank capacity (L): 636

Consumption (L/h): 87.2 at 75% of the load / 119.3 at 100% of the load

Running time (h): 7.3 at 75% of the load / 5.3 at 100% of the load

Length (mm): 3500

Width (mm): 1500

Height (mm): 2100

Dry weight (Kg): 3650

Silenced: No

Super silenced: No

---

ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Doosan