



# PRAMAC GSW10Y COFANATO CON QUADRO COMANDO MANUALE (MCP)

## Product description:

## Product features:

Phase: Three phase

Maximum power three phase (KW): 505.45

Continuous power three phase (KW): 458.3

Maximum power three phase (KVA): 631.81

Continuous power three phase (KVA): 572.87

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Engine: Doosan DP180LA, turbo intercooled

Speed governor: Electronic

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 18273

Cooling: Water

Alternator: Mecc Alte ECO40-1.5L/4, brushless

Poles: 4

Fuel tank capacity (L): 636

Consumption (L/h): 95.8 at 75% of the load / 129.8 at 100% of the load

Running time (h): 6.6 at 75% of the load / 4.9 at 100% of the load

Length (mm): 3500

Width (mm): 1500

Height (mm): 2100

Dry weight (Kg): 3900

Silenced: No

Super silenced: No

---

ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Doosan