



POWERMATE WX 3200 SINGLE PHASE GENERATOR 3.69 KVA AVR

Product price:

420,00 € tax excluded

Product description:

POWERMATE WX3200 SINGLE PHASE GENERATOR 3.69 KVA AVR

POWERMATE WX3200 is a single-phase generator equipped with a 4-stroke gasoline engine, capable of delivering a maximum power of 3,69 KVA complete with AVR voltage regulator.

The POWERMATE WX3200 is equipped with sturdy handles and wheels that allow easy portability; like the entire POWERMATE WX3200 range, it is a generator set that meets high quality standards and guarantees a high level of reliability.

The strong points of the POWERMATE WX3200 are: the high quality of the components, lightness, compactness, portability and ease of use and also the modern design. The single-phase 3KVA generator is equipped with a manual rope starter.

The POWERMATE WX3200 has been specially developed for camping, caravans, homes, and hobby applications, etc., so it reflects the special features and comfort that allow its reliability and convenience in the areas of application.

The POWERMATE WX3200 is also equipped with an hour meter, an oversized fuel tank for extended runtime and a rain cover for use in bad weather.

Advantages of the AVR voltage regulator

The automatic voltage regulator, or AVR, allows the single-phase generator 3KVA to deliver stable energy and then be able to connect equipment with delicate electronics such as computers, appliances, smartphones and tablets: the genset is therefore ideal for home use, camping, hobbies and leisure, but also for construction sites and craftsmen.





The AVR and the high quality alternator with copper windings will provide you with safe and stabilized energy.

Technical specifications of the POWERMATE WX 3200

Phase Type: SinglePhase

SinglePhase Continuous Power: 3.06 KVA / 2.45 KW SinglePhase Maximum Power: 3.69 KVA / 2. 95 KW

VAC voltage: 230 V Frequency (Hz): 50 Voltage regulator: AVR

Starting framework: Manual with self-winding

Engine: OHV 4-stroke

RPM: 3000

Power supply: Gasoline

Tank capacity: 17 I

Consumption @ 75 % of load: 1. 29 l/h Autonomy @ 75 % of load: 13.1 h Sound pressure: 65 dB(A) @ 7m

Length: 685 mm Width: 505 mm Height: 520 mm Net weight: 49 Kg

Are you looking for a generator with different technical characteristics? Here you can find the area dedicated to POWERMATE generators or other specialized brands

Images and data are not binding and may be subject to revisions.

Product features:

Phase: Single phase

Maximum power single phase (KW): 2.95 Continuous power single phase (KW): 2.45 Maximum power single phase (KVA): 3.69 Continuous power single phase (KVA): 3.06

Fuel: Gasoline Frequency (Hz): 50 Voltage (V): 230

Sockets configuration: 2 x 230V

Engine: OHV 4 tempi

Emissions Regulations: Stationary Use

Engine rpm (rpm): 3000





Speed governor: Mechanical Starting system: Pull starter

Cooling: Air

Fuel tank capacity (L): 17

Consumption (L/h): 1.3 at 75% of the load

Running time (h): 13.1 at 75% of the load / 10 at 100% of the load

Acoustic pressure: 65 dB(A) at 7 m

Length (mm): 685 Width (mm): 505 Height (mm): 520 Dry weight (Kg): 49

Silenced: No

Super silenced: No ATS Switch device: No Voltage regulator: AVR Engine manufacturer: OHV

