



# POWERMATE WX 6200 SINGLE PHASE GENERATOR 7.25 KVA AVR ELECTRIC STARTER

**Product price:**

**825,00 € tax excluded**

## **Product description:**

POWERMATE WX 6200 SINGLE-PHASE GENERATOR 7.25 KVA AVR

POWERMATE WX 6200 is a single-phase generator equipped with a 4-stroke gasoline engine with electric start, capable of delivering a maximum power of 7.25 KVA complete with AVR voltage regulator.

The POWERMATE WX 6200, is equipped with sturdy handles and wheels that allow easy portability; like the entire POWERMATE WX 6200 range, it is a generator set that meets a high quality standard and guarantees a high level of reliability.

The strengths of the POWERMATE WX 6200 are: the high quality of components, light weight, compactness, portability and ease of use and also modern design. The single-phase 7.25 KVA generator is equipped with a manual rope starter.

The POWERMATE WX 6200 has been specially developed for camping, caravans, homes, and hobby applications, etc., so it reflects distinctive features and convenience that allow it to be reliable and convenient in application areas.

The advantages of AVR

The automatic voltage regulator, or AVR allows the single-phase 7.25 KVA generator to deliver stable power and thus be able to connect equipment with sensitive electronics such as computers, household appliances, smartphones and tablets: the generator set is therefore ideal for use in the home, camping, hobby and leisure, but also for construction sites and craftsmen. The AVR voltage regulator and the other quality standard of the alternator with copper windings



will provide you with safe and stabilized power.

#### Technical Features of the POWERMATE WX 6200

Phase Type: Single-Phase  
Continuous Single-Phase Power: 6.63 KVA / 5.3 KW  
Maximum Single-Phase Power: 7.25 KVA / 5.8 KW  
VAC Voltage: 230 V  
Frequency (Hz): 50  
Voltage Regulator: AVR  
Starting Frame: Electric  
Engine: OHV 4-Stroke  
Emission Standard: Stage V  
RPM: 3000  
Power supply: Gasoline  
Fuel tank capacity: 26 l  
Consumption @ 75 % load: 2.17 l/h  
Autonomy @ 75 % load: 12 h  
Sound pressure: 69 dB(A) @ 7m  
Length: 800 mm  
Width: 698 mm  
Height: 620 mm  
Net weight: 89 Kg

Are you looking for a generator with different technical characteristics? Here you can find the area dedicated to POWERMATE generators or other specialized brands

Pictures and data are not binding and may be subject to revisions.

#### Product features:

Phase: Single phase  
Maximum power single phase (KW): 5.8  
Continuous power single phase (KW): 5.3  
Maximum power single phase (KVA): 7.25  
Continuous power single phase (KVA): 6.63  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230  
Engine: OHV 4-Stroke  
Emissions Regulations: Stage 5



---

Engine rpm (rpm): 3000  
Speed governor: Mechanical  
Starting system: Electric  
Cooling: Air  
Fuel tank capacity (L): 26  
Consumption (L/h): 2.16  
Running time (h): 12  
Acoustic pressure: 69 dB(A) at 7 m  
Length (mm): 800  
Width (mm): 698  
Height (mm): 620  
Dry weight (Kg): 89  
Silenced: No  
Super silenced: No  
ATS Switch device : No  
Voltage regulator: AVR

