



DOMETIC TEC 60 Petrol Single Phase Generator 7000 Watts 230 V AC Inverter

Product description:

Despite its continuous power of 6000 watts, it is surprisingly quiet and economical. Like all other TEC series generators, the speed varies according to requirements.

Proven inverter technology ensures pure sinusoidal voltage and high performance.

Quality characteristics

- Remote Control
- 12 V voltage for battery charger
- Automatic switch-off in case of low oil level
- Electric Ignition
- Overload and short circuit protection
- Sound absorbing housing
- High continuous power
- Suitable as a power source for all Dometic air conditioners
- Low consumption
- Remote control for displaying all the parameters of working
- Fueled with unleaded petrol

Certifications

EC, E13

Non-binding images and technical data.

Product features:

Phase: Single phase

Maximum power single phase (KW): 7

Continuous power single phase (KW): 6.2

Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230
Engine: Honda GX390
Starting system: Manual / Electric
Consumption (L/h): 3..7
Acoustic power: 90 dB(A)
Acoustic pressure: 66 dB(A) at 7 m
Length (mm): 626
Width (mm): 446
Height (mm): 547
Dry weight (Kg): 102
Silenced: Yes
Super silenced: Yes
Brushes: No
Voltage regulator: Inverter
Engine manufacturer: Honda