

# PRAMAC S8000 SINGLE PHASE



Product price:

**2.869,50 € tax excluded**

## Product description:

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

## Product features:

Phase: Single phase

Maximum power single phase (KW): 6.4

Continuous power single phase (KW): 5.5

Maximum power single phase (KVA): 7.2

Continuous power single phase (KVA): 6

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 2P+T CEE - 1 x 230V 32A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: Honda GX390 Electric, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 389

Oil capacity (L): 1.1

Cooling: Air

Poles: 2



---

Fuel tank capacity (L): 26.5  
Consumption (L/h): 2.14 at 75% of the load / 2.87 at 100% of the load  
Running time (h): 12.38 at 75% of the load / 9.23 at 100% of the load  
Acoustic power: 97 dB(A)  
Acoustic pressure: 73 dB(A) at 7 m  
Length (mm): 840  
Width (mm): 615  
Height (mm): 753  
Dry weight (Kg): 109  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : Optional  
Voltage regulator: Capacitor  
Engine manufacturer: Honda

