



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 9.6

Maximum power single phase (KVA): 12

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE

Engine: Honda GX690R

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 688

Number cylinders: 2

Oil capacity (L): 1.9

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 4.6 at 100% of the load

Running time (h): 4.34 at 100% of the load

Acoustic power: 100 dB(A)

Acoustic pressure: 75 dB(A) at 7 m

Length (mm): 990

Width (mm): 550

Height (mm): 670

Dry weight (Kg): 130

Silenced: No

Super silenced: No

ATS Switch device : Optional
Voltage regulator: No
Engine manufacturer: Honda