



## WFM SE12000-MTHE AVR

## **Product description:**

## **Product features:**

Phase: Single phase

Maximum power single phase (KW): 3.6 Maximum power single phase (KVA): 4.5

Fuel: Gasoline Frequency (Hz): 50 Voltage (V): 230

Sockets configuration: 1 x 230V 16A - 1 x 230V 16A CEE

Engine: Honda GX270 Engine rpm (rpm): 3000 Starting system: Electric Engine capacity (cm³): 270

Number cylinders: 1 Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 6

Consumption (L/h): 2.4 at 100% of the load Running time (h): 2.5 at 100% of the load

Acoustic power: 95 dB(A)

Acoustic pressure: 70 dB(A) at 7 m

Length (mm): 780 Width (mm): 520 Height (mm): 560 Dry weight (Kg): 70

Silenced: No

Super silenced: No





ATS Switch device: No Voltage regulator: No Engine manufacturer: Honda

