



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase
Maximum power single phase (KW): 5.6
Maximum power single phase (KVA): 7
Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230
Sockets configuration: 1 x 230V 16A - 1 x 230V 16A CEE
Engine: Honda GX390
Engine rpm (rpm): 3000
Starting system: Electric
Engine capacity (cm³): 389
Number cylinders: 1
Oil capacity (L): 1.1
Cooling: Air
Fuel tank capacity (L): 6.5
Consumption (L/h): 3.1 at 100% of the load
Running time (h): 2.09 at 100% of the load
Acoustic power: 96 dB(A)
Acoustic pressure: 71 dB(A) at 7 m
Length (mm): 780
Width (mm): 520
Height (mm): 560
Dry weight (Kg): 81
Silenced: No
Super silenced: No

ATS Switch device : No

Voltage regulator: No

Engine manufacturer: Honda