



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 1.8

Maximum power single phase (KVA): 2.2

Maximum power three phase (KW): 4.3

Maximum power three phase (KVA): 5.4

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE - 1 x 230V 16A 3P SCHUKO

Engine: Honda GX270

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 270

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 2.4 at 100% of the load

Running time (h): 8.33 at 100% of the load

Acoustic power: 95 dB(A)

Acoustic pressure: 70 dB(A) at 7 m

Length (mm): 750

Width (mm): 560

Height (mm): 620

Dry weight (Kg): 82

Silenced: No

Super silenced: No

ATS Switch device : Optional

Voltage regulator: No

Engine manufacturer: Honda