



# WFM SE12000-MTHE AVR

## Product description:

## Product features:

Phase: Single phase

Maximum power single phase (KW): 5.6

Maximum power single phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A - 1 x 230V 16A CEE

Engine: Honda GX390

Engine rpm (rpm): 3000

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm<sup>3</sup>): 389

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 3.1 at 100% of the load

Running time (h): 6.45 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 71 dB(A) at 7 m

Length (mm): 750

Width (mm): 560

Height (mm): 620

Dry weight (Kg): 86

Silenced: No

---

Super silenced: No  
ATS Switch device : No  
Voltage regulator: No  
Engine manufacturer: Honda