



## WFM SE12000-MTHE AVR

### Product description:

### Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 3

Maximum power single phase (KVA): 3.8

Maximum power three phase (KW): 5

Maximum power three phase (KVA): 6.3

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 32A 5P CEE - 1 x 230V 16A 3P CEE

Engine: Yanmar L100AE

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 406

Number cylinders: 1

Oil capacity (L): 2

Cooling: Air

Fuel tank capacity (L): 5.5

Consumption (L/h): 2 at 100% of the load

Running time (h): 2.75 at 100% of the load

Acoustic power: 103 dB(A)

Acoustic pressure: 78 dB(A) at 7 m

Length (mm): 780

Width (mm): 520

Height (mm): 560

Dry weight (Kg): 115

Silenced: No

Super silenced: No

ATS Switch device : No

Voltage regulator: No

Engine manufacturer: Lombardini