



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 4.8

Maximum power single phase (KVA): 6

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V - 1 x 230V CEE

Engine: Honda GX390

Engine rpm (rpm): 3000

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 389

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 6.5

Consumption (L/h): 3.1 at 100% of the load

Running time (h): 2.09 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 71 dB(A) at 7 m

Length (mm): 780

Width (mm): 520

Height (mm): 560

Dry weight (Kg): 73

Silenced: No

Super silenced: No
ATS Switch device : No
Voltage regulator: AVR
Engine manufacturer: Honda