



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 4.8

Maximum power single phase (KVA): 6

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE - 1 x 230V 16A 3P SCHUKO

Engine: Honda GX390

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 389

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 3.1 at 100% of the load

Running time (h): 6.45 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 71 dB(A) at 7 m

Length (mm): 750

Width (mm): 560

Height (mm): 620

Dry weight (Kg): 83

Silenced: No

Super silenced: No
ATS Switch device : Optional
Voltage regulator: AVR
Engine manufacturer: Honda