



WFM SE12000-MTHE AVR

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 8

Maximum power single phase (KVA): 10

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 3P CEE - 1 x 230V 32A 3P CEE

Engine: Honda GX690

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm³): 690

Number cylinders: 2

Oil capacity (L): 1.8

Cooling: Air

Fuel tank capacity (L): 20

Consumption (L/h): 5.8 at 100% of the load

Running time (h): 3.44 at 100% of the load

Acoustic power: 92 dB(A)

Acoustic pressure: 67 dB(A) at 7 m

Length (mm): 1070

Width (mm): 560

Height (mm): 920

Dry weight (Kg): 210

Silenced: Yes

Super silenced: Yes

ATS Switch device : Optional
Voltage regulator: AVR
Engine manufacturer: Honda