

# TECNOGEN H2700



## Product description:

GENERATOR TECNOGEN LD7500E 5,6 KW

Generator TECNOGEN LD7500E singlephase power of 5,6 KW with Lombardini engine of 3000 rpm with diesel feeding. The TECNOGEN LD7500E generating set is very simple to use and is compact, easy to handle and maintain. The TECNOGEN LD7500E generating set is equipped with electric start. This genset is ideal for hobby use but also for professional use, thanks to the reliable Lombardini engine with diesel power supply and to all the high quality components it is composed of.

## Why buy a LD7500E genset ?

First of all, it solves problems of lack of electricity during black-outs in different environments, from homes to companies. The TECNOGEN LD7500E generator set is also used to provide electricity on construction sites and for hobby use. Professional generators are light machines, easy to transport, compact and robust, simple to use and with low running costs. They present, moreover, an excellent quality/price ratio.

On the TECNOGEN LD7500E generator set it is possible to install lifting hooks, very convenient to move the current generator with an overhead crane or a small crane.

## The following are the main features:

Maximum single-phase power: 5.6 KW

Maximum single-phase power: 7 KVA

Fuel: Diesel

Voltage: 230V

Engine: Lombardini 15LD440

Boosting: Electric

Length: 780 mm

Width: 520 mm

Height: 560 mm

Weight: 101 Kg

### All TECNOGEN range

TENOGEN generator sets are available in both single-phase and three-phase versions, with powers from 2.3 to 21 KVA MAX, equipped with gasoline or diesel engines, air-cooled, 3000 rpm, electric start and/or manual start with recoil starter. Compact, simplified and economical, they boast an excellent price/performance/size/weight ratio. Easily transportable thanks to the reduced dimensions due to an essential equipment, they are suitable for all those who need an economic source of energy, however, assembled with first-class components that ensure absolute reliability. TECNOGEN gasoline versions of COMPACT line, thanks to the Honda engines of the latest generation, fall within the parameters of the noise directive 2000/14/EC.

Are you looking for a different model of current generator or generator set? Visit the section dedicated to land based generators.

Images and technical data are not binding.

### Product features:

Phase: Single phase

Maximum power single phase (KW): 5.6

Maximum power single phase (KVA): 7

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230

Engine: HONDA GC160

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 442

Number cylinders: 1

Cooling: Air

Fuel tank capacity (L): 5

Consumption (L/h): 1.6

Running time (h): 3.1

Length (mm): 780

Width (mm): 520

Height (mm): 560

Dry weight (Kg): 101

Silenced: No

Super silenced: No

ATS Switch device : Optional

Voltage regulator: AVR (optional)

---

Engine manufacturer: Lombardini