



GREEN POWER GP16A-PW-C OPEN

Product price:

6.184,00 € tax excluded

Product description:

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

You can choose between the versions:

- Open group with Compound-Linz alternator (automatic power pack)
- -Open group with AVR-Leroy alternator (automatic power pack)
- -Open group with AVR-Mecc Alte alternator (automatic power pack)
- -Open group with AVR-Stamford alternator (automatic power pack)

The image is purely indicative.

Product features:

Phase: Three phase

Maximum power three phase (KW): 4.4





Continuous power three phase (KW): 4 Maximum power three phase (KVA): 5.5 Continuous power three phase (KVA): 5

Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 230 / 400

Engine: PERKINS 403A-15G1, 4 stroke naturally aspirated

Emissions Regulations: NON EMISSIONATO

Engine rpm (rpm): 1500 Speed governor: Mechanical Starting system: Elettrico Engine capacity (cm³): 686

Number cylinders: 3

Cylinders' position: In line

Cooling: Water

Alternator: Linz E1S13ME/4, synchronous, with brushes

Poles: 4

Protection degree: IP21 Fuel tank capacity (L): 60

Consumption (L/h): 2.8 al 75% del carico

Running time (h): 21.72 Length (mm): 1500 Width (mm): 700 Height (mm): 1020

Silenced: No

Super silenced: No

ATS Switch device: Optional

Voltage regulator: Compound / AVR (optional)