



# TELAIR ENERGY 4010D WITH AUTOMATIC CONTROL PANEL



## Product description:

### TELAIR ENERGY 4010D GENERATOR WITH AUTOMATIC CONTROL PANEL

TELAIR ENERGY 4010D vehicular generator with 3.4 KW automatic control panel is a new generation, very low fuel consumption, single-phase 230 V single-phase **supersilenced** generator with Hatz diesel engine.

Can be installed by connecting directly to the diesel vehicle's fuel tank, thus eliminating any auxiliary tanks. The TELAIR ENERGY 4010D is built with a metal container with double soundproofing that greatly reduces noise emissions. It can be provided with a completely automatic electronic starting system with remote control panel with 5 meters of cable equipped with: total and partial hours counter, engine temperature control lights, oil and gas oil level.

The automatic control panel allows the control in automatic motion of the generator simplifying the operations on the panel. The TELAIR ENERGY 4010D also has a built-in 12 V / 10 A battery charger. Removable bottom drawer for easy maintenance of the TELAIR ENERGY 4010D.

The TELAIR ENERGY 4010D has a design able to integrate itself to the perfection on every type of motorhome both in its external shape and with every particular of the inside furnishing. A continuous technical innovation fruit of a long experience, renewed and projected into the future by the enthusiasm, the fantasy and the competence of a team of young designers.

The TELAIR ENERGY 4010D is built with materials of excellent quality and subjected to various tests to ensure maximum durability.

In addition, the group is contained in a metal case soundproofed with highly insulating materials, so as to further reduce the noise level and make it possible to use even when there are other vehicles in the vicinity. The sturdy metal structure is equipped with an extractable drawer that allows easy access to the generator to carry out mechanical maintenance operations in a practical and safe manner.



---

## THE TECHNICAL CHARACTERISTICS TELAIR ENERGY 4010D

Phase Type: Single Phase  
Maximum Power: 3.4 KW  
Continuous Power: 3.2 KW  
Voltage: 230 V  
Frequency: 50 Hz  
Motor: HATZ 1B30 V  
Fuel: Diesel  
Start: Electric  
Fuel Consumption: 1. 6 lt/h  
Acoustic Pressure: 66 dBA @ 7m  
Width: 415 mm  
Length: 690 mm  
Height: 391 mm  
Weight: 98 Kg

Browse through our extensive catalog of vehicular generators to find the right vehicular generator for your needs like the TELAIR.

Images and technical data are not binding.

### **Product features:**

Phase: Single phase  
Maximum power single phase (KW): 3.4  
Fuel: Diesel  
Frequency (Hz): 50  
Voltage (V): 230  
Engine: Hatz 1B30V  
Starting system: Electric  
Alternator: Synchronous  
Poles: 2  
Consumption (L/h): 0.9  
Acoustic pressure: 63 dB(A) at 7 m  
Length (mm): 690  
Width (mm): 415  
Height (mm): 390  
Dry weight (Kg): 98  
Inverter: No  
AVR: No  
Compound: No  
Silenced: Yes

---

Super silenced: Yes  
Product type: Generator  
Voltage regulator: No  
Engine manufacturer: Hatz