

# STANLEY SG 5500



## Product description:

## Product features:

Phase: Single phase / Three phase  
Maximum power three phase (KW): 5.5  
Continuous power three phase (KW): 3.6  
Maximum power three phase (KVA): 6.88  
Continuous power three phase (KVA): 4.5  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: 1 x 400V - 3 x 230V  
Engine: CP188F, 4 stroke  
Engine rpm (rpm): 3000  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 389  
Number cylinders: 1  
Oil capacity (L): 1.1  
Cooling: Air  
Alternator: Synchronous  
Fuel tank capacity (L): 25  
Consumption (L/h): 2.73  
Running time (h): 9.15  
Acoustic power: 97 dB(A) a 4 m  
Length (mm): 730  
Width (mm): 590  
Height (mm): 595  
Dry weight (Kg): 91



---

Inverter: No  
AVR: Yes  
Compound: No  
Silenced: No  
Super silenced: No

