



# STANLEY SG 5500



## Product description:

## Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 5.5

Continuous power three phase (KW): 3.6

Maximum power three phase (KVA): 6.88

Continuous power three phase (KVA): 4.5

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V - 3 x 230V

Engine: CP188F, 4 stroke

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 389

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Alternator: Synchronous

Fuel tank capacity (L): 25

Consumption (L/h): 2.73

Running time (h): 9.15

Acoustic power: 97 dB(A) a 4 m

Length (mm): 730

Width (mm): 590

Height (mm): 595

Dry weight (Kg): 91



Inverter: No

AVR: Yes

Compound: No

Silenced: No

Super silenced: No