

PRAMAC E5000 SINGLE PHASE



Product price:

1.124,25 € tax excluded

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 4.6

Continuous power single phase (KW): 3.9

Maximum power single phase (KVA): 5.1

Continuous power single phase (KVA): 4.2

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A IP54 SCHUKO - 1 x 230V 16A IP44 2P+T CEE

Engine: Honda GX270 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 270

Oil capacity (L): 1.1

Cooling: Air

Alternator: Brushless

Poles: 2

Fuel tank capacity (L): 5.3

Consumption (L/h): 1.6 at 75% of the load / 2.2 at 100% of the load

Running time (h): 3.2 at 75% of the load / 2.4 at 100% of the load

Acoustic power: 97 dB(A)

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 715

Width (mm): 540
Height (mm): 490
Dry weight (Kg): 61
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: Capacitor
Engine manufacturer: Honda