



# PRAMAC E6000 DIESEL THREE PHASE



Product price:

**2.572,50 € tax excluded**

## Product description:

Motori diesel Yanmar. Raffreddamento ad aria. Avviamento a strappo . Alternatore sincrono. Robusta struttura con telaio tubolare portante. Prese su cuffia con protezioni termiche.

L'immagine è puramente indicativa

## Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.2

Continuous power single phase (KW): 2.8

Maximum power single phase (KVA): 4

Continuous power single phase (KVA): 3.5

Maximum power three phase (KW): 5.5

Continuous power three phase (KW): 4.5

Maximum power three phase (KVA): 6.9

Continuous power three phase (KVA): 5.7

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T SCHUKO - 1 x 230V 16A 2P+T SCHUKO

Engine: Yanmar L100N, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter



---

Engine capacity (cm<sup>3</sup>): 435  
Oil capacity (L): 1.6  
Cooling: Air  
Alternator: With brushes  
Poles: 2  
Fuel tank capacity (L): 5.5  
Consumption (L/h): 1.45 at 75% of the load / 1.9 at 100% of the load  
Running time (h): 3.8 at 75% of the load / 2.8 at 100% of the load  
Length (mm): 760  
Width (mm): 540  
Height (mm): 560  
Dry weight (Kg): 96  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: Compound  
Engine manufacturer: Yanmar