



PRAMAC E6000 DIESEL THREE PHASE



Product price:

2.572,50 € tax excluded

Product description:

Motori diesel Yanmar. Raffreddamento ad aria. Avviamento a strappo . Alternatore sincrono. Robusta struttura con telaio tubolare portante. Prese su cuffia con protezioni termiche.

L'immagine è puramente indicativa

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 3.2

Continuous power single phase (KW): 2.8

Maximum power single phase (KVA): 4

Continuous power single phase (KVA): 3.5

Maximum power three phase (KW): 5.5

Continuous power three phase (KW): 4.5

Maximum power three phase (KVA): 6.9

Continuous power three phase (KVA): 5.7

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T SCHUKO - 1 x 230V 16A 2P+T SCHUKO

Engine: Yanmar L100N, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter



Engine capacity (cm³): 435

Oil capacity (L): 1.6

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 5.5

Consumption (L/h): 1.45 at 75% of the load / 1.9 at 100% of the load

Running time (h): 3.8 at 75% of the load / 2.8 at 100% of the load

Length (mm): 760

Width (mm): 540

Height (mm): 560

Dry weight (Kg): 96

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: Compound

Engine manufacturer: Yanmar