



PRAMAC ES8000 SINGLE PHASE

Product price:

1.905,00 € tax excluded

Product description:

Product features:

Phase: Single phase

Maximum power single phase (KW): 6.4

Continuous power single phase (KW): 5.5

Maximum power single phase (KVA): 7.2

Continuous power single phase (KVA): 6

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A SCHUKO IP54 - 1 x 230V 32A 2P+T CEE IP44

Engine: Honda GX390 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 389

Oil capacity (L): 1.1

Cooling: Air

Poles: 2

Fuel tank capacity (L): 11

Consumption (L/h): 2.1 at 75% of the load / 2.9 at 100% of the load

Running time (h): 5.1 at 75% of the load / 3.8 at 100% of the load

Acoustic power: 97 dB(A)

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 729

Width (mm): 500



Height (mm): 536
Dry weight (Kg): 73
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: Capacitor
Engine manufacturer: Honda