



MOSA GE S-7000 BBM ELECTRIC STARTER

Product price:

1.855,00 € tax excluded

Product description:

Gasoline generator with Briggs&Stratton engine, electric starter. Single phase power 5 KW.

Features:

- Electric Start
- Engine shut down for low oil level
- Circuit breaker
- Fuel level gauge
- Protective frame and partially covered
- Silenced
- Portable
- Meets EC directives for safety
- AVR version on request

The image is purely indicative.

Product features:

Phase: Single phase

Maximum power single phase (KW): 6

Continuous power single phase (KW): 5

Maximum power single phase (KVA): 6.7

Continuous power single phase (KVA): 5.5

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 32A 2P+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A 2P+T SCHUKO



Engine: Briggs&Stratton XR2100, 4 stroke, OHV
Engine rpm (rpm): 3000
Speed governor: Mechanical
Starting system: Electric
Engine capacity (cm³): 420
Number cylinders: 1
Oil capacity (L): 1.1
Cooling: Air
Alternator: Synchronous self-excited, self-regulated, brushless
Bore x stroke (mm): 90 x 66
Fuel tank capacity (L): 20
Consumption (L/h): 2.7 at 75% of the load
Running time (h): 10.5 at 75% of the load
Acoustic power: 99 dB(A)
Acoustic pressure: 74 dB(A) at 7 m
Length (mm): 770
Width (mm): 520
Height (mm): 650
Dry weight (Kg): 104
Silenced: Yes
Super silenced: No
ATS Switch device : No
Voltage regulator: No
Engine manufacturer: Briggs&Stratton