



# CGM 25NG GAS METANO - APERTO CON CENTRALINA MANUALE

## Product description:

## Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 22

Continuous power three phase (KW): 20

Maximum power three phase (KVA): 27.5

Continuous power three phase (KVA): 25

Fuel: Natural Gas

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 63A 5P - 1 x 230V 16A 3P

Engine: General Motors RMG 3000

Engine rpm (rpm): 1500

Speed governor: Electronic

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 3000

Number cylinders: 4

Cylinders' position: In line

Cooling: Water

Alternator: Marelli, brushless

Poles: 4

Bore x stroke (mm): 101.6 x 91.4

Natural Gas consumption (m<sup>3</sup>/h): 10 at 100% of the load

Length (mm): 1500

Width (mm): 900

Height (mm): 1500

Dry weight (Kg): 700



Silenced: No

Super silenced: No

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: General Motors