



SINCRO FK2 MGA Single Phase Synchronous AC Alternator 13.5 kVA AVR

Product description:

Single phase brushes alternator - AVR.

- Self-regulated
- IP23
- Standard voltage 230 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

Product features:

Phase: Single phase

Frequency (Hz): 50

Voltage (V): 230

Engine rpm (rpm): 3000

Poles: 2

Single-phase power (KW): 13.5

Single-phase power (KVA): 13.5

Efficiency (%): 82.5

Protection degree: IP23

Dry weight (Kg): 64

Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: AVR