



# SINCRO ET2 LAF Three Phase Synchronous AC Alternator 8.5 kVA Compound

## Product description:

Three phase brushes alternator - Compound.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 22.14 / cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE
- With reinforced phase

The image is purely indicative.

## Product features:

Phase: Single phase / Three phase

Frequency (Hz): 50

Voltage (V): 230 / 400

Engine rpm (rpm): 3000

Poles: 2

Single-phase power (KW): 4

Single-phase power (KVA): 5

Three-phase power (KW): 6.8

Three-phase power (KVA): 8.5

Efficiency (%): 83

Protection degree: IP23

Dry weight (Kg): 37



Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: Compound