

SINCRO FTR2 LC Three Phase Synchronous AC Alternator 24 kVA D-AVR



Product description:

Three phase brushes alternator - DIGITAL AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE
- DIGITAL AVR

The image is purely indicative.

Product features:

Phase: Three phase
Frequency (Hz): 50
Voltage (V): 230 / 400
Engine rpm (rpm): 3000
Poles: 2
Three-phase power (KW): 19.2
Three-phase power (KVA): 24
Efficiency (%): 87
Protection degree: IP23
Dry weight (Kg): 82
Brushes: Yes
Type of alternator: Constant Speed
Voltage regulator: Digital AVR

