



# SINCRO FT4 MCS Three Phase Synchronous AC Alternator 11 kVA Compound

## Product description:

Three phase brushes alternator - Compound.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

## Product features:

Phase: Three phase

Frequency (Hz): 50

Voltage (V): 230 / 400

Engine rpm (rpm): 1500

Poles: 4

Three-phase power (KW): 8.8

Three-phase power (KVA): 11

Efficiency (%): 81

Protection degree: IP23

Dry weight (Kg): 50

Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: Compound

