

# SINCRO FTR4 LC Three Phase Synchronous AC Alternator 17 kVA D-AVR



## Product description:

Three phase brushes alternator - DIGITAL AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE
- DIGITAL AVR

The image is purely indicative.

## Product features:

Phase: Three phase  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Engine rpm (rpm): 1500  
Poles: 4  
Three-phase power (KW): 13.6  
Three-phase power (KVA): 17  
Efficiency (%): 84  
Protection degree: IP23  
Dry weight (Kg): 68  
Brushes: Yes  
Type of alternator: Constant Speed  
Voltage regulator: Digital AVR

