



## SINCRO IB2 SB SINGLE-THREE PHASE ALTERNATOR 33KVA AVR

## **Product description:**

Three phase brushless alternator - AVR.

- Insulation class H
- IP23
- Standard voltage 230/400 V 50 Hz
- Leads 6
- Bearings: Bearings are dimensioned for heavy duty
- Transient features: Transient voltage drop for rated step load at 0.8 power factor is less than 18%
- Single-phase operation: IB2 alternators can be connected for single-phase use

The image is purely indicative.

## **Product features:**

Phase: Single phase / Three phase

Frequency (Hz): 50 Voltage (V): 230 / 400 Engine rpm (rpm): 3000

Poles: 2

Single-phase power (KW): 15.84 Single-phase power (KVA): 19.8 Three-phase power (KW): 26.4 Three-phase power (KVA): 33

Efficiency (%): 85.3 Protection degree: IP23





Dry weight (Kg): 117

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR

